



tradeSELECT™

## IMPORTANT

The battery in this unit may not be fully charged. After electricity is connected to the unit, let battery charge up to 24 hours. Then the normal operation of this unit should take effect. To check press the “TEST” button and the lights on the unit should turn ON

## IMPORTANT SAFEGUARDS

When using electrical equipment, basic safety precautions should always be followed including the following.

### READ AND FOLLOW ALL SAFETY INSTRUCTIONS

1. Do not use outdoors.
2. Do not mount near gas or electric heater.
3. Use caution when handling batteries. Avoid possible shorting.
4. Equipment should be mounted at heights to prevent tampering by unauthorized personnel.
5. The use of accessory equipment is not recommended by the manufacturer, this may cause unsafe conditions.
6. Do not use this equipment for other than the intended use.
7. Save these instructions.

### INSTALLER:

- SEE UNIT LABEL FOR ADDITIONAL MODEL SPECIFICATIONS
- SAVE THESE INSTRUCTIONS FOR USE BY OWNER/OCCUPANT

**WARNING** – This product contains chemicals known to the State of California to cause cancer, birth defects and/or other reproductive harm. Thoroughly wash hands after installing, handling, cleaning, or otherwise touching this product.

## IMPORTANT

When relamping, only use lamps specified in the exit sign. Using other lamp types may result in transformer damage or unsafe conditions. Battery in this unit may not be fully charged.

After electricity is hooked up to unit, let the battery charge up for at least 24 hours. Then normal operation of this unit should take effect



#### RECYCLING INFORMATION

All steel, aluminum and thermoplastic parts are recyclable. All cartons contain recycled materials.  
Please recycle responsibly.

Hubbell Lighting, Inc. Life Safety Products • [www.compasslightingproducts.com](http://www.compasslightingproducts.com)

© 2017 Hubbell Lighting, Inc., All Rights Reserved • Specifications subject to change without notice. • Printed in U.S.A.

COM604091\_CCRCSD\_INST\_SHT 11/17

### Conduit Mounting

1. Connect 20" jumper leads to A.C. input leads in J-box, fasten J-box bracket to Jbox. Use Black wire for 120 volt, Red wire for 277 volt, White wire is common.
2. Fasten canopy to J-box bracket
3. Snap housing to canopy
4. Connect and trim input leads to socket leads at upper left corner of housing wire channel.
5. Mount two Remote lamp heads at most.
6. Secure faceplate to housing. Remove the proper arrow as required.

### Back Mounting

1. Connect 20" jumper leads to AC input leads in J-box. Use Black wire for 120 volt, Red wire for 277 volt, White wire is common.
2. Remove necessary knockouts and fasten back cover to J-box.
3. Snap housing to back cover.
4. Connect and trim input leads to socket leads at upper left corner of housing wire channel.
5. Mount two Remote lamp head at most.
6. Secure face plate housing.

OPERATION

1. During an electrical power failure, the lamps on the unit will automatically come ON for a minimum of 90 minutes.
2. To test this unit, let it charge correctly with AC power supply for a minimum of 24 hours after its first installation and then depress the "TEST" switch, the emergency lamps will illuminate. When the switch is released, the lamps will turn OFF.
3. For the unit with Self-Diagnostic, must connect as below:
  - 1)When customer doesn't need remote lamp,please insert terminal to N.(See Figure 1 below)
  - 2) When customer needs remote lamp,please insert terminal to Y.( See Figure 2 below)

Figure 1



Figure 2

