

## IMPORTANT SAFEGUARDS

When using electrical equipment, basic safety precautions should always be followed including the following.

### READ AND FOLLOW ALL SAFETY INSTRUCTIONS

1. Do not use outdoors.
2. Do not mount near gas or electric heater.
3. Use caution when handling batteries. Avoid possible shorting.
4. Equipment should be mounted at heights(Max:9ft) to prevent tampering by unauthorized personnel.
5. The use of accessory equipment is not recommended by the manufacturer, this may cause unsafe conditions.
6. Do not use this equipment for other than the intended use.
7. Save these instructions

### IMPORTANT:

**When relamping, only use lamps specified in the exit sign. Using other lamp types may result in transformer damage or unsafe conditions.**

**WARNING** – This product contains chemicals known to the State of California to cause cancer, birth defects and/or other reproductive harm. Thoroughly wash hands after installing, handling, cleaning, or otherwise touching this product.

tradeSELECT®

## INSTALLATION

### Ceiling Mounting

1. Connect 20" jumper leads to A.C. input leads in J-box, fasten J-box bracket to J-box.
2. Use Black wire for 120 volt, Red wire for 277 volt, White wire is common.
3. Fasten canopy to J-box bracket.
4. Snap housing to canopy.
5. Connect and trim input leads to socket leads at upper left corner of housing wire channel.
6. Secure face plate to housing. Remove the proper arrow as required.


### Back Mounting

1. Connect 20" jumper leads to A.C. input leads in J-box. Use Black wire for 120 volt, Red wire for 277 volt, White wire is common.
2. Remove necessary knockouts and fasten back cover to J-box.
3. Snap housing to back cover.
4. Connect and trim input leads to socket leads at upper left corner of housing wire channel.
5. Secure face plate to housing.

### WARNING:

**Unused wires must be capped using enclosed wire nuts.**

## WIRING DIAGRAM



**RECYCLING INFORMATION**  
All steel, aluminum and thermoplastic parts are recyclable. All cartons contain recycled materials. Please recycle responsibly.