



*Commercial, Industrial
and Residential Electrical Products*

4 In. Square Box, Welded, 2-1/8 Deep, Nine 1/2 In. KO's & Five TKO's, BOX-LOC® MS Bracket, Flush

Catalog #:
238



FEATURE BENEFIT

Square boxes are used where multiple conductor runs are split into two or more directions to bring power to a number of electrical devices. Built in bracket or supports speeds installation. Box-Loc bracket is a snap to install on site. It crimps as you press the bracket on, quickly locking in place.

PRODUCT FEATURES

- MS style BOX-LOC® bracket, flush
- Combination screw heads allow quick installation
- Welded construction
- Nine 1/2 In. knockouts and Five TKO knockouts
- UL Listed
- 30.3 Cu. In. capacity
- RACO 978
- Acceptable in 2-hour fire rated walls

APPLICATIONS

Designed to enclose electrical wiring, switches, receptacles or lighting fixtures. Constructed from 1/16 In. pre-galvanized steel. 8-32 cover mounting screws assembled. Suitable for use without a bonding jumper in circuits up to 600V.

CERTIFICATIONS



PRODUCT SPECIFICATIONS

UPC Number:	050169002384
Ea Length/Depth (in.):	2.188
Ea Width (in.):	5.50
Ea Height (in.):	4.625
Wt. Ea. (Lbs.):	1.052
Package Type:	Loose
Product UPC-A Labeled:	Yes

PACKAGING

Case I2of5:	50050169002389
Standard Carton Qty:	25
Min Order Qty:	25



All RACO single-gang, two-gang, 4 In. square, and single gang gangable U.L. listed steel boxes are acceptable for use in 2-hour fire rated walls. For additional information, consult U.L. "Fire Resistance Directory" or the U.L. website at www.ul.com

600V Per UL 514-A, suitable for use without a bonding jumper in circuits up to 600 volts

Revision 1, March 2020



**COMMERCIAL
CONSTRUCTION**
A Division of Hubbell Incorporated (Delaware)

RACO
3902 W. Sample St.
South Bend, IN 46619
574-234-7151
www.hubbell.com/raco/en

