
ORDERING INFORMATION

ORDERING EXAMPLE: LNC2-P25-4K-FT-U-DB-SCP-8F





- 1 Must specify voltage (120 or 277 only for E & EH)
- Must order minimum of one remote control to program dimming settings, 0-10V fully adjustable dimming with automatic daylight calibration and different time delay settings, 120-277V only
- 3 PCU option not applicable, included in sensor


8F Up to 8ft mount height

20F Up to 20ft mount height

DIMENSIONS








Standard Unit

With Sensor Options



With Battery Backup

A	В	C	D	E	WEIGHT STD.	WEIGHT SENSOR	WEIGHT WTIH BBU
5.54"	10.16"	6.33"	7.64"	9.10"	7.0 lbs.	7.5 lbs.	9.5 lbs.
40.7mm	258 mm	160.7mm	194mm	231mm	3.2 kg	3.4 kg	4.3 kg



FOR MORE INFORMATION ABOUT LNC2 PRISMATIC:



ALERA LIGHTING HUBBELL INDUSTRIAL LIGHTING

ARCHITECTURAL AREA LIGHTING HUBBELL OUTDOOR LIGHTING

BEACON PRODUCTS KIM LIGHTING COLUMBIA LIGHTING **KURT VERSEN** COMPASS LITECONTROL DUAL-LITE PRESCOLITE

HUBBELL CONTROL SOLUTIONS

Due to our continued efforts to improve our products, product specifications are subject to change without notice.

WHITEWAY

H0L0034 May 24, 2018 4:56 PM



LTTEPAK LNC2 PRISMATIC REFRACTOR WALLPACK

HUBBELL HUBBELL Outdoor Lighting

The award winning Litepak LNC2 luminaire now features an industry leading prismatic refractor option for the ultimate combination of performance and visually appealing perimeter illumination. Additionally, the LNC2 can be specified with energy saving controls and/ or egress options. The Litepak LNC2 luminaire is available in multiple lumen packages providing safety, security and identity.

- Prismatic refractor lens for optimal visual comfort and performance
- Optional photocell, occupancy sensor and battery backup
- Optional Four ½" threaded surface conduit entries
- IP65 rated
- DLC qualified*





Specially design prismatic refractor lens provides improved visual comfort and superior light output and performance.

Quick Mounting

Quick-mount – easy mounting without opening fixture. Attach adapter plate to wall, connect wires, hang fixture and tighten set screws.




Optional factory installed top mounted button photocontrol.



PERFORMANCE

10' Mounting Height - LNC2-P35-4K-FT











EGRESS/BATTERY BACK UP

