





## SystemOne Recessed 6 Inch FRPT and Covers, for Use In Concrete Floors





| Description   | Catalog Number |
|---|----------------|
| 6 Inch Fire-Rated Poke-Through.                                 | S1R6PTFIT      |
| 6 Inch Fire-Rated Poke-Through; for use in the City of Chicago. | S1R6PTFITCHI   |

Note: See page P-36 for technical information.

## **Recessed 6 Inch Covers**

6 Inch FRPT cover assembly unit includes solid cast aluminum construction, carpet gasket and mounting hardware. All covers are UL514A, scrubwater compliant. Furniture Feed covers include (1) 2" Threaded Hub & (1) 3/4" Threaded Hub.



















| Cover Finish          | Catalog Number | Furniture Feed Option |
|-----------------------|----------------|-----------------------|
| Brushed Aluminum      | S1R6CVRALU     | S1R6FFCVRALU          |
| Black Powder Coat     | S1R6CVRBLK     | S1R6FFCVRBLK          |
| Brushed Brass Plated  | S1R6CVRBRS     | S1R6FFCVRBRS          |
| Antique Bronze Plated | S1R6CVRBRZ     | S1R6FFCVRBRZ          |
| Gray Powder Coat      | S1R6CVRGRY     | S1R6FFCVRGRY          |
| Satin Nickel Plated   | S1R6CVRNKL     | S1R6FFCVRNKL          |

Note: COVER LOAD RATING: 1,000 lbs with 2x safety factor. Load applied through a 3 in. (76) mandrel at the center of the cover. Static loads only.



S1R6SPEXT

## **6 Inch Accessories**

| Description   | Catalog Number |
|---|----------------|
| Pre-pour tube, includes hardware.   | S1R6PPT*       |
| Abandonment plate, black finish.  | S1R6ADMTBK     |
| Low voltage replacement divider.  | S1R6DIV        |
| Power junction box, 27.0 cubic inches; (1) ¾ inch and (1) 1 inch EMT connector. | S1FRPTJB       |
| Replacement 1½ inch extension kit, ships with 6" FRPT kits and S1R6PTFIT(CHI)   | S1R6SPEXT      |
| Power junction box  | S1FRPTJB2      |
|   |                |

Note: \*Not UL Listed.



**Replacement Furniture Feed Fitting** 

| Description                    | Catalog Number |
|--------------------------------|----------------|
| 2 inch furniture feed fitting. | S1RFFFIT2      |

S1RPLUG2ALU

S1RPLUG075ALU

| Replacement Plugs | 3 |
|-------------------|---|
| Finish            |   |
|                   |   |

| 110   111   1 |             |               |
|---|-------------|---------------|
| Finish  | 2 Inch      | 3/4 Inch      |
| Brushed Aluminum  | S1RPLUG2ALU | S1RPLUG075ALU |
| Black Powder Coat   | S1RPLUG2BLK | S1RPLUG075BLK |
| Brushed Brass Plated  | S1RPLUG2BRS | S1RPLUG075BRS |
| Antique Bronze Plated   | S1RPLUG2BRZ | S1RPLUG075BRZ |
| Satin Nickel Plated   | S1RPLUG2NKL | S1RPLUG075NKL |