

Key Benefits

- Available in seven different finishes
- Water and tamper-resistant face
- Compact shallow design minimizes space in cabinet
- cULus Listed for countertop installation
- Easy push-down to pop-up function is rated for a minimum of 10,000 cycles (OPEN/CLOSE)
- Permanent installation ready (suitable for AC90 or NMD 90 wire)

Before Installing the Countertop Receptacle:

Different components will be used throughout the installation including the housing, base, countertop flange, receptacle cover, locking nut and installation screws.







Step 1

Cut a circular hole approximately 4" in diameter in the countertop.

Then, determine what colour silicone top to use, peel off the protective tab to expose adhesive surface on the pop-up tower, snap on that cover. For black colour RCT600BK & RCT620BK and white colour RCT600W & RCT620W, skip this step, go to step 2.



Step 2

Remove the base from the housing to expose screw terminals.



Step 3

CAUTION:

Before handling the cable, make sure the circuit is OFF.

Place the tightening ring on the cable whip before wiring the device.

Feed cable through the lock nut under the countertop, as this will secure the device later.



Step 4

Fasten the metal jacket to the device base. A fitting will be required (not included).







Step 5

Strip conductors to the correct length as shown on the device.

Ground the base by bonding the green or bare wire to the grounding screw on the base.

Terminate the green or bare wire to the green screw marked. Terminate the white or gray wire to the white screw marked "WHITE" and black or red wire to the brass screw marked "HOT".



Step 6

Reattach the base to the housing and secure with screws.



Step 7

Insert the device into the countertop opening and hand tighten the locknut to secure it in place.



Step 8

Terminate the device to the power source. Press the cover to pop up the receptacle to use, press again to close.











Quick Installation Setup Guide

Because Spills Happen

Hubbell countertop receptacles are spill test compliant

COUNTERTOP RECEPTACLES

Description	Finish	Color/ Material	15A 125V Receptacle		20A 125V Receptacle	
			Surface Mount	Flush Mount	Surface Mount	Flush Mount
Tamper-resistant pop-up kitchen counter receptacle, rated for 20A circuits Cover: machined aluminum, wiring chamber accepts AC90 or NMD wire	Powder Coated	Black White Bronze	RCT200BK RCT200W RCT200BZE	RCT201BK RCT201W RCT201BZE	RCT220BK RCT220W RCT220BZE	RCT221BK RCT221W RCT221BZE
	Brushed	Aluminum Brass Nickel	RCT200ALU RCT200BR RCT200NI	RCT201ALU RCT201BR RCT201NI	RCT220ALU RCT220BR RCT220NI	RCT221ALU RCT221BR RCT221NI
	Polished	Chrome	RCT200CH	RCT201CH	RCT220CH	RCT221CH
Tri-power AC, includes: tamper-resistant pop-up kitchen counter receptacle, USB Type AC and wireless inductive, rated for 20A circuits Cover: machined aluminum, wiring chamber accepts AC90 or NMD wire	Powder Coated	Black White Bronze	RCT600BK RCT600W RCT600BZE	_ _ _	RCT620BK RCT620W RCT620BZE	_ _ _
	Brushed	Aluminum Brass Nickel	RCT600ALU RCT600BR RCT600NI	_ _ _	RCT620ALU RCT620BR RCT620NI	_ _ _
	Polished	Chrome	RCT600CH	_	RCT620CH	_





