

# 4 In. Square Box, Welded, 2-1/8 In. Deep, Nine 1/2 In. KO's and Five TKO's, FM Bracket

Catalog #: 237



## FEATURE BENEFIT

Square boxes are used where multiple conductor runs are split into two or more directions to bring power to a number of electrical devices. Built in bracket or supports speeds installation.

### **PRODUCT FEATURES**

- FM style bracket, flush
- · Combination screw heads allow quick installation
- Welded construction
- Nine 1/2 in. knockouts and Five TKO knockouts
- UL Listed
- 30.3 cubic inch capacity
- · Acceptable in 2-hour fire rated walls

#### **APPLICATIONS**

Designed to enclose electrical wiring, switches, receptacles or lighting fixtures. Constructed from 1/16 In. pre-galvanized steel. 8-32 cover mounting screws assembled. Suitable for use without a bonding jumper in circuits up to 600V.

#### **CERTIFICATIONS**



#### **PRODUCT SPECIFICATIONS**

UPC Number: Ea Length/Depth (in.): Ea Width (in.): Ea Height (in.): Wt. Ea. (Lbs.): Package Type: Product UPC-A Labeled: 050169002377 2.336 4.403 7.625 1.106 Loose Yes

#### PACKAGING

Case I2of5: Standard Carton Qty: Min Order Qty: 50050169002372 25 25



RACO 3902 W. Sample St. South Bend, IN 46619 574-234-7151 www.hubbell.com/raco/en





All RACO single-gang, two-gang, 4 In. square, and single gang gangable U.L. listed steel boxes are acceptable for use in 2-hour fire rated walls. For addtional information, consult U.L. "Fire Resistance Directory" or the U.L. website at www.ul.com

600V Per UL 514-A, suitable for use without a bonding jumper in circuits up to 600 volts

Revision 1, March 2020



©2020 Hubbell. All rights reserved. Information subject to change. Trademarks are property of their respective owners.

RA\_SPEC-SHEET