BELL RACO C HUBBELL .

4-11/16 IN. TWO DEVICE COVERS, PARTITIONS, AND FIXTURE COVERS

4-11/16 in. Square Two Device and Tile Covers Raised 1-1/2 in.



Catalog #: 885

APPLICATIONS

RACO 4-11/16" raised device covers are for mounting switches or receptacles Low voltage partitions may be added to conduit-type boxes to divide power from voice/data Partitions must be used with raised covers

PRODUCT FEATURES

Partition divides 4" square boxes into two compartments Use partitions with two-device covers which have a slot for the partition Helpful hint: Assemble the box with the partition in place before breaking off at the scored tab. This will prevent you from breaking off more tab than needed

UL LISTED

File E195978

CSA

File LR-1082

GENERAL PRODUCT INFORMATION

CONFIGURATION

Drawn or Welded:	Welded
Raised (in.):	1-1/2 in
PRODUCT MEASUREMENTS Cubic Inches (cm3): Wt. Ea. (Lbs.): Product Length (in.): Product Width (in.): Product Width (in.):	15.5 (254.0) 0.628 1.50 4.69 4.69
PACKAGING	20
Minimum Pack Qty.:	20
Std. Pkg.:	No
Product UPC-A Labeled:	62.80
Weight (Lbs. Per/C):	11.13
Ship Carton Length (in.):	8.50
Ship Carton Height (in.):	10.00
Chi Weight (Lbs.):	12.56
Pallet Qty:	1600
UPC Number:	050169008850
I2of5:	50050169008855

Page 1 / 1

