

# **Turnbuckle**

By ANDERSON Catalog # TB112JJ18

"Turnbuckles are used as adjustable extensionlinks to maintain proper tower clearance onassemblies at tower end. Jaw ends are supplied with bolt, nut, andhumpback cotter pin. Add "LN" suffix if jam nuts are required."



## **Features**

- "Turnbuckle, 1-1/2", Jaw-Jaw, Forged Steel, Diameter = 1.5", Take Up = 18.00" and Ult. Strength = 107,000 LBS
- The torque required to rotate the bossof a turnbuckle under tension can be calculated by the formula:
- T = 2 (kdW/12) ft-lb
- Where: k = Friction factor (0.16)
- d = Nominal thread diameter (inches)
- W = Applied tension load (lb)
- Example: 1-1/2" turnbuckle under 4,000 lb tension
- $T = 2(0.16 \times 1.5 \times 4000 / 12) = 160 \text{ ft-lb}''$

#### General

Material	Steel
Material - Pin (Clevis)	Galvanized Steel
Number of Bolt Holes	0
Series	TYPE JJ
Strength Rating - Ultimate	107000 lb
Strength Rating - Ultimate Body	O lb
With Jam Nuts	No

#### **Dimensions**

Assembly Rating (Ultimate)	0 lb
Diameter - Bolt	0 in
Diameter - Pin	0 in
Insulator Throat Diameter - Maximum	O in
Insulator Throat Diameter - Minimum	0 in
Insulator Throat Diameter Range	0 - 0
Length - Pin	0 in
Maximum Adjustment	0 in
Ring Height	0 in
Take Up	18 in
Weight	36.750 lb

#### **Conductor Related**

Conductor Diameter -	0 in
Maximum	
Conductor Spacing	O in

### **Product Assets**

Catalogs - Transmission Connectors Catalog - Full (CA05063E)

