# austdac<sup>®</sup>

# RED ALERT® VoIP Emergency Telephones - Model 397-710

By Austdac Pty Ltd Catalog # 397-710

GAI-TRONICS' RED ALERT\* Hands-free VoIP Flush-Mount Telephones are designed to provide direct point-to-point communications between personnel throughout a facility over an existing internet protocol LAN. The VoIP telephones are intended for connection to a 10/100 BaseT Ethernet and operate using power-over-Ethernet or an alternative power source. The VoIP telephone features real-time alarm reporting that enables system supervisors to monitor the phone's activity and address callers needs or maintenance issues immediately.



## **Application**

Emergency Telephone Communcations (campuses, parking lots, paths)

Silver

#### General

Color

Type

Connectivity Options VoIP Construction Front Panel: 14-Gauge Type 304 Brushed Stainless Steel; Dust Cover: 16-Gauge Cold-Rolled Steel With Black Polyurethane Finish Mount location Flush-Mount Operating Temperature -4°F to +131°F / -20°C to +55 °C Output Level Speaker 87 dB @ 1 M VoIP - SIP

Signal Type

VoIP - SIP

Storage Temperature Range

-40° C to +70° C

Temperature Rating

VoIP - SIP

-40° C to +70° C

-4°F to +131°F (-20°C to

+55°C)

• HELP Button

• Emergency Telephones

Weather Rating Type 3R

#### **Dimensions**

 Dimensions
 2.38 in x 10.0 in x 12.0 in

 Height
 12.0 in

 Length
 2.38 in

 Weight
 7.2 lb

 Width
 10.0 in

#### **Electrical Ratings**

Signal Ethernet

Voltage Rating Description 24-48 VDC or PoE

### **Certifications and Compliance**

Certification UL/CSA/FCC
Certified Listed UL/CSA/FCC
Compliance FCC CRF 47 Part 15

#### **Product Assets**

Brochures - Red Alert Telephone Brochure Configuration Guide - VoIP Telephone Basic Configuration

Guide Guide - Vol P Telephone Basic Configuration Guide

Configuration Guide - VoIP Telephone Configuration Guide: Firmware versions 1193 Telephones (v1.08); 1201 Telephones for Auteldac 6 (v1.08)

Installation Manuals - RED ALERT® Hands-free VoIP Telephone Manual

Literature - VoIP Hands-free Telephones - Flush-mount