


FD67CG39, Substation - Copper Stud Connector

By Burndy Catalog # FD67CG39



Features

- High copper alloy stud connector allows bolting cable and tubing terminals to equipment studs
- Hex head captured bolts provide one-wrench installation
- One pad contact surface is on centerline of stud, pad is finished on both sides, all pads are 4-hole NEMA drilling

Application

Substation

General

Catalog Number FD67CG39
Connector Type Stud Connector
Installation Torque 360 lbs-in

Recommended in-lb

Material Copper Alloy, Cast

Material - Hardware Durium

Physical Attribute - Number of

Holes

Physical Attribute - Pad 3.5x3.75 - 4 holes

Configuration

Physical Attribute - Pad In-line

Orientation

Plated

Plating Type Unplated Type Studs

UPC 781810450444 UPC 12 Digit 7818104504444

Dimensions

Dimension - B Length inch 2.62 in
Dimension - Bolt Size fraction 1/2
Dimension - D inch 3.75 in

Dimension - F Width Center to	1.75 in
Center inch	
Dimension - Height mm	0 mm
Dimension - L Length Overall	187 mm
mm	
Dimension - Length Overall	7.38 in
inch	
Dimension - N inch	0.88 in
Dimension - Pad Width inch	3.50 in
Dimension - Pin Diameter inch	1.50 in
Dimension - Threads per inch	12
Dimension - Width inch	3.50 in

Conductor Related

Conductor - Connection Stud to Pad

Combination

Certifications And Compliance

Certification - CSA Approved	No
Certification - ETL	No
Certification - UL Recognized	No
Certification - cULus	No
Standards - RoHS Compliance	CM
Status	
UL Listed	No

Logistics

Minimum Pack Quantity 4

Product Assets

Catalogs - BURNDY Master Catalog - Full Line BURNDY Catalog Customer Notices - Prop 65 Notice Interactive Catalog - BURNDY Full-Line Digital Catalog Sales Drawings - CSC032410-01 Specifications - FD67CG39

