



## QB26, Right Angled Heavy Duty Copper Lug Connector, 1/0-2/0 AWG Str, 3/8" Stud, 1 Screw

By Burndy  
Catalog # [QB26](#)



Copper Terminal, Side Entrance, 1 Hole, 1/0-2/0 AWG (Str), 3/8" Stud, 1 Screw.

### Features

- Side Entry terminal
- Joins a range of cable at right angles to terminal blocks
- One-wrench installation

### Application

For Joining A Range Of Copper Cable At Right Angles To Terminal Blocks

### General

|  |                         |
|--|-------------------------|
| Catalog Number                                   | QB26                    |
| Connector Type                                   | Right Angle             |
| EU RoHS Indicator                                | Yes                     |
| Installation Torque                              | 180 LBS/in              |
| Recommended in-lb                                |                         |
| Material   | Copper                  |
| Physical Attribute - Number of Clamping Elements | 1                       |
| Physical Attribute - Number of Holes             | 1                       |
| Physical Attribute - Number of Screws            | 1                       |
| Physical Attribute - Screw Type                  | Hexagonal Bolt          |
| Plated   | N                       |
| Plating Type                                     | Unplated                |
| Sub Brand  | QIKLUG                  |
| Trade Name                                       | QIKLUG™                 |
| Type   | Bolted Lugs & Terminals |
| UPC  | 781810324288            |

### Dimensions

|                                |          |
|--------------------------------|----------|
| Dimension - B Length fraction  | 47/50 in |
| Dimension - B Length inch      | 0.94 in  |
| Dimension - Bolt Size fraction | 3/8      |
| Dimension - D inch             | 1.00 in  |
| Dimension - Height fraction    | 1-1/8    |
| Dimension - Height inch        | 1.13 in  |
| Dimension - Height mm          | 28.7 mm  |
| Dimension - Hole Size fraction | 13/32    |
| Dimension - Hole Size inch     | 0.41 in  |
| Dimension - Hole Size mm       | 10 mm    |

|                                 |          |
|---------------------------------|----------|
| Dimension - L Length Overall mm | 46 mm    |
| Dimension - Length Overall inch | 1.81 in  |
| Dimension - N inch              | 0.44 in  |
| Dimension - Pad Width fraction  | 13/16 in |
| Dimension - Pad Width inch      | 0.81 in  |
| Dimension - Stud Size fraction  | 3/8      |
| Dimension - Stud Size inch      | 3/8      |
| Dimension - Width inch          | 0.81 in  |
| Dimension - Width mm            | 21 mm    |
| Weight                          | 0.23 lb  |

### Conductor Related

|                                   |               |
|-----------------------------------|---------------|
| Conductor - Copper Str Size       | 1/0 ;2/0 AWG  |
| Conductor - Copper Str Size Range | 1/0 -2/0 AWG  |
| Conductor Size                    | 1/0-20 AWG    |
| Conductor Type                    | CU C Str-Size |
| Number of Conductors              | 1             |

### Certifications And Compliance

|                                    |              |
|------------------------------------|--------------|
| Buy American Compliant             | Yes          |
| Certification - CSA Approved       | No           |
| Certification - ETL                | No           |
| Certification - UL Recognized      | No           |
| Certification - cULus              | No           |
| Industry Standard(s)               | UL 486A-486B |
| Standards - Industry Standards Met | UL 486A-486B |
| Standards - RoHS Compliance Status | EX           |
| UL Listed                          | Yes          |

### Logistics


|                       |   |
|-----------------------|---|
| Minimum Pack Quantity | 1 |
|-----------------------|---|

### Product Assets

[3D Models - QB26\\_MODEL-PDF](#)  
[3D Models - QB26\\_MODEL-STEP](#)  
[3D Models - QB26\\_MODEL-IGES](#)

[Catalogs - BURNDY Master Catalog - Section A - Mechanical](#)  
[Catalogs - BURNDY Master Catalog - Full Line BURNDY Catalog](#)  
[Customer Notices - Prop 65 Notice](#)  
[Interactive Catalog - BURNDY Full-Line Digital Catalog](#)

[Product Cross Section Image\(s\) - BUR\\_QB\\_LineArt](#)  
[Sales Drawings - sa06068-01](#)  
[Specifications - QB26](#)



©2024 Hubbell Incorporated. All rights reserved  
BRDY-QB26-SPEC-EN | REV 10/2024