

UH195B, Substation Copper Bus Support

By Burndy Catalog # UH195B

Application

Copper Bus Connectors.



*Representative Image

		Combination	
Substation		Conductor - Copper Tube EH	2 1/2 IPS IPS
		Size	
General		Conductor - Copper Tube EH	2 1/2 IPS IPS
Catalog Number	UH195B	Size Range	
Connector Type	Bus Support	Conductor - Copper Tube Std	2 1/2 IPS IPS
Fitting Type	Slip or Rigid	Size	
Hardware Type	Base mounting kit (w nuts)	Conductor - Copper Tube Std	2 1/2 IPS IPS

Hardware Type Base mounting kit (w nuts) Material Copper Alloy

Material - Hardware DURIUM™ Silicon Bronze

Mounting Hardware 5/8-11 x 1 3/4" LG

One Wrench Installation Plated Ν

Plating Type Unplated

Туре Cable or Tube to Insulator Bus

Supports

UPC 781810119709 UPC 12 Digit 7818101197099

Dimensions

Bolt Circle Diameter 5 in Dimension - G inch 3.13 in Dimension - Height inch 5.00 in Dimension - Hole Size fraction 11/16 Dimension - Hole Size inch 0.69 in Dimension - Width inch 5.25 in Dimension - Width mm 133 mm

Conductor Related

Conductor - Connection	Base to Tube
Combination	
Conductor - Copper Tube EH	2 1/2 IPS IPS
Size	
Conductor - Copper Tube EH	2 1/2 IPS IPS
Size Range	
Conductor - Copper Tube Std	2 1/2 IPS IPS
Size	
Conductor - Copper Tube Std	2 1/2 IPS IPS
Size Range	
Conductor Type	 CU Tube Std-Size
	 CU Tube EH-Size
Number of Conductors	1

Certifications And Compliance

Certification - CSA Approved	
Certification - ETL	No
Certification - UL Recognized	No
Certification - cULus	
Standards - RoHS Compliance	
Status	
UL Listed	No

Logistics

Minimum Pack Quantity

Product Assets

Catalogs - BURNDY Master Catalog - Full Line BURNDY Catalog Customer Notices - Prop 65 Notice Interactive Catalog - BURNDY Full-Line Digital Catalog Specifications - UH195B

