



## B1001

by Burndy  
Catalog ID: B1001

Mold, Horizontal Cable Tap To Horizontal Lug, 500 kcmil, 200 Weld Metal, 1/4" 1-1/2" Lug.

Features: Type BCB-1 Molds Are Used To Connect A Copper Conductor To A Copper Lug Or Bus Bar, Size Range Is 8 AWG Through 1000 MCM Concentric Stranded Copper Conductors, Conductor Type: Concentric Stranded Copper, Recommended Accessories: B38-3922-00 Mold Cleaning Brush, B38-0135-00 Cable Cleaning Brush, Cartridge Type: Standard, Lug Size: 1/4 X 1-1/2 IN, Required Tools: B38-0309-00 Flint Ignitor

## Product Details

### General

Application	For Connecting A Copper Conductor To A Copper Lug Or Bus Bar
Sub Brand	BURNDYWELD
Trade Name	BURNDYWeld®
Type	Molds
UPC	781810392263
UPC 12 Digit	7818103922633

### Conductor Related

Conductor - Copper Str Size	500 kcmil
Conductor Type	CU C Str-Size

### Certifications and Compliance

Standards - RoHS Compliance Status	CM
------------------------------------	----

### Logistics

Minimum Pack Quantity	1
-----------------------	---

**For further technical assistance, please contact us**

**BURNDY Headquarters**  
47 East Industrial Park Drive  
Manchester, New Hampshire 03109

**Customer Service Hours:**  
8 AM - 8 PM Eastern Monday-Friday  
Emergency Service 24-hours/365 Days  
Phone: 1-800-346-4175  
1-603-647-5299 (International)