



## B975

by Burndy  
Catalog ID: B975

Mold, Horizontal Cable Tap to Horizontal Lug or Bus, 2 AWG, 45 Weld Metal, 1/8" 1" Lug.

Features: Type BCB-1 Molds Are Used To Connect A Copper Conductor To A Copper Lug Or Bus Bar, Size Range Is 8 AWG Through 1000 MCM Concentric Stranded Copper Conductors, Conductor Type: Concentric Stranded Copper, Recommended Accessories: B38-3922-00 Mold Cleaning Brush, B38-0135-00 Cable Cleaning Brush, Cartridge Type: Standard, Lug Size: 1/8 X 1 IN, Required Tools: B38-0309-00 Flint Ignitor

## Product Details

### General

Application	For Connecting A Copper Conductor To A Copper Lug Or Bus Bar
Sub Brand	BURNDYWELD
Type	Molds
UPC	781810396919
UPC 12 Digit	7818103969199

### Dimensions

Dimension - Bus Bar Size Tap Side inch	1/8" X 1"
--	-----------

### Conductor Related

Conductor - Copper Str Size	2 AWG
Conductor Type	CU C Str-Size

### Certifications and Compliance

Standards - RoHS Compliance Status	CM
------------------------------------	----

### Logistics

Minimum Pack Quantity	1
-----------------------	---

**For further technical assistance, please contact us**

**BURNDY Headquarters**  
47 East Industrial Park Drive  
Manchester, New Hampshire 03109

**Customer Service Hours:**  
8 AM - 8 PM Eastern Monday-Friday  
Emergency Service 24-hours/365 Days  
Phone: 1-800-346-4175  
1-603-647-5299 (International)