



B984

by Burndy
Catalog ID: B984

Mold, Horizontal Cable Tap to Horizontal Lug or Bus, 4/0 AWG, 90 Weld Metal, 3/16" 1" Lug.

Features: Type BCB-1 Molds Are Used To Connect A Copper Conductor To A Copper Lug Or Bus Bar, Size Range Is 8 AWG Through 1000 MCM Concentric Stranded Copper Conductors, Recommended Accessories: B38-3922-00 Mold Cleaning Brush, B38-0135-00 Cable Cleaning Brush, Conductor Type: Concentric Stranded Copper, Cartridge Type: Standard, Lug Size: 3/16 X 1 IN, Required Tools: B38-0309-00 Flint Ignitor

Product Details

General

Application	For Connecting A Copper Conductor To A Copper Lug Or Bus Bar
Sub Brand	BURNDYWELD
Type	Molds
UPC	781810397091
UPC 12 Digit	7818103970911

Dimensions

Dimension - Bus Bar Size Tap Side inch	3/16" X 1"
--	------------

Conductor Related

Conductor - Copper Str Size	4/0 AWG
Conductor Type	CU C Str-Size

Certifications and Compliance

Standards - RoHS Compliance Status	CM
------------------------------------	----

Logistics

Minimum Pack Quantity	1
-----------------------	---

For further technical assistance, please contact us

BURNDY Headquarters
47 East Industrial Park Drive
Manchester, New Hampshire 03109

Customer Service Hours:
8 AM - 8 PM Eastern Monday-Friday
Emergency Service 24-hours/365 Days
Phone: 1-800-346-4175
1-603-647-5299 (International)