RH Opening, 25kV, 125kV BIL, 900A 3 Phase By-Pass Switch with **Pole Mounting Bracket**

By CHANCE Utility Catalog # BP3R6PZ

Righthand Opening, 25kV, 125kV LIW, 900A By-Pass Switch with Pole Mounting Bracket.



*Representative Image

Features

- Fully Compliant with ANSI/IEEE C37.30.1
- 15, 27 and 3 kV ratings
- 110, 125 and 150kV BIL ratings
- 600A and 900A ratings
- ESP Polymer 2.25" Bolt Circle Insulator Assemblies
- · Right Hand and Left Hand opening Options
- Non-Angled and Angled Bypass Blade Options
- Cross arm or Pole Mount Options
- 3 Phase on 100" or 124" Cross Arms in Steel or Fiberglass

General

Blade Type Solid Copper (two blade

truss-member)

Cantilever Bending Strength -1,000 Lbs (4.45kN)

Routine

Color - Insulator Dark Gray Contact Silver

Polymer (2 1/4" Bolt Circle) Insulator Type

Material - Base Galvanized Steel per ASTM

A190

Tension Range 5000 lb

3,000 in Lbs (339 N-M) Torsional Strength

Dimensions

460 lb Weight

Electrical Ratings

Arc Distance - Dry 8.1" (205.7mm)

BIL 125 kV

Creep and Leakage Distance 21.9" (556.3mm)

Current Overload - 8hr 1080 A

Emergency

Phase Three Phase

Reference Voltage Limit -25kV

Minimum

Temperature Rise - Max. at 33° C

600A

29 kV Voltage - Maximum

Withstand Current - Short 25kA, symmetrical

Time (1 sec)

Withstand Current - Short 65kA peak

Time (10 cycles)

Certifications and Compliance

Industry Standard(s) All Applicable ANSI/IEEE

Standards

Logistics

Standard Package

Product Assets

Catalogs - Hookstick Operated Switches (CA10230E 14B) Installation Manuals - BP3 Instructions (TD10321E Rev. B -

Literature - SF11041E Type BP3 Switch

Sales Drawings - 3-Phase, By-Pass, 3 Pull Switch

(PSSABP3WXYZ)

