CHANCE®

22/36.4 kV, 150 kV BIL, Type C Linkbreak Porcelain Cutout / Arrester Combination w/100A 12kAIC fuseholder

By CHANCE Utility
Catalog # C72EN313LXS

22/36.4 kV, 150 kV BIL, Linkbreak Type C Porcelain Cutout / Arrester Combination with a 100A, 12kAIC fuseholder, large eyebolt connector and an extended NEMA "B" crossarm bracket.

Features

- Fully Compliant with ANSI/IEEE C37.41 & C37.42 2016
- Interchangeable with ABB Type ICX & S&C(MPS) Type XS
- Single Vent Solid Cap Design
- Uses Universal Style Fuse Links
- Synthetic Arc Quenching Fuse Holder Liner Material
- Ohio Brass Distribution Class Arresters in Standard, Heavy and Riser Pole Duty Ratings

General

Bracket Type	Extended NEMA "B" for
	crossarm
Corrosion Resistant?	Yes
Description - Replacement	T720-313T

Fuse Holder

Type Cutout



*Representative Image

Electrical Ratings

BIL	150 kV
Creep and Leakage Distance	17.3" (440mm)
Current Rating	100 A
Fuselink Current Range	1A to 100A - removable buttonhead fuse link only
Reference Voltage Limit -	No Restrictions thru 20.8kV; *22.8 thru 34.5kV

35° C

Temperature Rise - Max. at

300A

Voltage - Radio Interference Ambient @22kV Voltage Rating 22/36.4 kV

Logistics

Standard Package

Product Assets

Experience (VI10004E)

Catalogs - Type C-Porcelain Cutouts (10A) Literature - Switching Line Card_FAQ_2019 Technical Solutions - CH-C72EN313LXS-SPEC-EN Video - Hubbell Power Systems Cutout Seminar, Part 2:

Video - Hubbell Power Systems Cutout Seminar, Part 3: Quality (VI10005E)