

# 15 kV, 110 kV BIL, Type C Loadbreak Porcelain Cutout / Arrester Combination w/100A 16kAIC fuseholder

By CHANCE Utility Catalog # C73EM114LX

15 kV, 110 kV BIL, Loadbreak Type C Porcelain Cutout / Arrester Combination with a 100A, 16kAIC fuseholder, large eyebolt connector and an extended NEMA "B" crossarm bracket.

### Features

- Fully Compliant with ANSI/IEEE C37.41 & C37.42 2016
- Interchangeable with ABB Type ICX & S&C(MPS) Type XS
- Single Vent Solid Cap Design
- Uses Universal Style Fuse Links
- Synthetic Arc Quenching Fuse Holder Liner Material
- Ohio Brass Distribution Class Arresters in Standard, Heavy and Riser Pole Duty Ratings
- Non Interchangeable Mounting Assembly

### General

Bracket Type	Extended NEMA "B" for crossarm
Description - Replacement Fuse Holder	T730-114T
Туре	Cutout



\*Representative Image

## **Electrical Ratings**

BIL	110 kV
Creep and Leakage Distance	8.7″ (220mm)
Current Rating	100 A
Fuselink Current Range	1A to 100A - removable buttonhead fuse link only
Reference Voltage Limit - Minimum	Thru 14.4kV
Temperature Rise - Max. at 300A	39° C
Voltage - Maximum	15 kV
Voltage - Radio Interference	Ambient @ 9.41kV
Voltage Rating	15 kV
Logistics	

Standard Package

#### **Product Assets**

Catalogs - Type C-Porcelain Cutouts (10A) Literature - Switching Line Card\_FAQ\_2019 Sales Drawings - 110KV BIL Loadbreak Cutout/Arrester (SA73DL1)

Video - Hubbell Power Systems Cutout Seminar, Part 2: Experience (VI10004E)

Video - Hubbell Power Systems Cutout Seminar, Part 3: Quality (VI10005E)

1

