KILLARK[®]

FXSX43 - XSD/XSX/FXSD/FXSX Series - FXSX Single Gang Aluminum Manual Motor Starting Switch - 3 Pole 3 Phase - Feed-Thru - Hub Size 1/2 In

By Killark Catalog # FXSX43

XSD/XSX/FXSD/FXSX Series - FXSX Single Gang Aluminum Manual Motor Starting Switch - 3 Pole 3 Phase - Feed-Thru - Hub Size 1/2 In

Features

- 0
- •
- •
- 0
- •
- •
- •
- •

General

Catalog NumberFXSX43EU RoHS IndicatorContact ManufacturerHorsepower - Maximum5MaterialAluminum, Copper Free (less
than 4/10 of 1%)SeriesFXSXUPC783936198088

Dimensions

Dimensions	8.25 in x 6 in x 6.75 in
Gross Weight with Packaging	4.56
Height	6.75 in
Length	8.25 in
Width	6 in



*Representative Image

Electrical Ratings

Frequency Rating	60 Hz
Voltage Rating	600 V

Certifications And Compliance

CSA File Number	LR11714
Hazardous Rating(s)	Class I, Divisions 1 & 2,
	Groups C, D
	Class I, Zones 1 & 2, Groups
	IIB, IIA
	Class II, Divisions 1 & 2,
	Groups E, F, G
	Class III, Divisions 1 & 2
Nema Rating	3
UL File Number	E53360 / E12379

Product Assets

Catalogs - Killark Catalog

Certifications - FXS & XS Series Motor Starters UL Certification Customer Notices - Prop 65 Notice Specifications - FXSX43 Specification Sheet French Specifications - FXSX43 Specification Sheet English Specifications - XSD/XSX & FXSD/FXSX Series Manual Motor Starters Specification Sheet

