

PRC™ Oil-Free Series Bushing - 15kV

By PCORE Electric Catalog # PRC110F3000B

PRC* 15kV-3000A Transformer-Circuit Breaker Bushing, Oil-Free Paper-Resin-Capacitor Type, Rated per IEEE C57.19.01, Bottom Connected for Air-to-Oil Applications, 16.50" Min. Oil Immersion Level



*Representative Image

Application

Transformer-Oil Circuit Breaker

General

Bottom Terminal Type Threaded
Color Gray
Immersion Type - Above Flange
Immersion Type - Below Oil

Number of Flange Mounting 6 Holes Number of Sheds 4 Test Tap Yes

Top Terminal Plating Silver Plated
Top Terminal Type Threaded

Type Condenser Bushings

Dimensions

Above Flange Length 16.25 in 24.50 in Below Flange Length Diameter - Above Flange 10.25 in Maximum Diameter - Below Flange 5.00 in Maximum D <gt/> 1" Diameter - Below Flange 5.25 in Maximum P Diameter - Bottom Terminal 3-12 Outside Diameter - Live Part Top 6.75 in Diameter - Top Terminal 3-12 Outside Effective Length - Bottom 3.00 in Terminal Effective Length - Top 3.00 in Terminal Flange Mounting Hole Bolt 9.25 in Circle Flange Mounting Hole 0.88 in Diameter

10.62 in

40.75 in

16 EO in

Flange Outside Diameter

Cround Shiold

Length

Electrical Ratings

BIL	110 kV
Current Rating	3000 A
Minimum Creepage	20.5 in
Minimum Strike	9.00 in
kV Class	15 kV

Certifications and Compliance

Industry Standard(s) IEEE

Product Assets

Installation Manuals - Instruction Manual for PRC® Bushings (B-303339 rev 07-14-20) Literature - Oil-Free PRC Bushings - PCORE (SF02024E) Sales Drawings - PRC Bushing Oil-Free (PRC110_3000B)

Related Products

B-63037-AF - Seismically Enhanced Test (SET) Terminal - 3000A

Length - Live Part Top 5.69 in
Length - Minimum Oil 16.50 in
Immersion Level
Sealing Surface Outside 8.25 in
Diameter
Thickness - Flange Plate 0.75 in



Weight

A proud member of the Hubbell Family.

115 lb

©2024 Hubbell Incorporated. All rights reserved. PCOR-PRC110F3000B-SPEC-EN | REV 1/2024