

One-Light Bath & Vanity

Project:

Fixture Type: Location:

Contact:

Wall mounted • Damp location listed PROGRESS LED



Description:

Images:

Arch LED is an innovative series of acrylic LED wall sconces that optimizes aesthetic appeal. One-light LED bath with AC LED module. Screen-printed lens accessories - in fabric linen or nature-inspired patterns - can be inserted into the fixtures for a unique effect. A perforated metal mesh end cap diffuses light above and below the fixture to provide even illumination.

Specifications:

- · Brushed Nickel (-09) (plated)
- Steel Construction
- White acrylic diffuser
- LED Module is replaceable (part # 93053641)
- Acrylic LED wall sconces- bath bracket.
- Perforated metal mesh end cap.
- 1,211 lumens 71.2 lumens/watt per module (source)
- 3000K color temperature, 90+ CRI.
- Dimmable to 10% brightness (See Dimming Notes)
- Back plate covers a standard 4" octagonal recessed outlet box
- Mounting strap for outlet box included
- 6" of wire supplied
- ENERGY STAR[®] qualified

Performance:

		Dimo
Number of Modules	1	Dime
Input Power	17w	Width Depth Heigh H/CTF Glass Width Length Heigh
Input Voltage	120 V	
Input Frequency	60 Hz	
Lumens/LPW (Delivered)	497.49/30.9 (LM-79)	
ССТ	3000 K	
CRI	90 CRI	
Life (hours)	60,000 (L70/TM-21)	
FCC	Meets FCC Title 47, Part 15 Class B	
Min. Start Temp	-30 °C	
Warranty	5 year warranty	
Labels	cCSAus Damp location listed	
	ENERGY STAR [®] qualified	



P2061-0930K9

Dimensions:

Width: 7-1/4" Depth: 3" Height: 6" H/CTR: 3"

Glass Width: 2-3/16" Length: 6-13/16" Height: 6"



One-Light Bath & Vanity

Wall mounted • Damp location listed PROGRESS LED



P2061-0930K9

Dimming Notes:

P2061 is designed to be compatible with many ELV/Reverse Phase controls.

The following is a partial list of known compatible dimmer controls.

Dimming Controls

Lutron Nova T NTELV-300

Lutron Vierti VTELV-600

Lutron Maestro MAELV-600

Lutron spacer/system SPSELV-600

Leviton Renoir II AWRMG-EAW

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.