

LED Mini-Pendant

 Ceiling stem mounted • Dry location listed 

Description:

One-light mini-pendant with a bold and striking Prismatic Glass shade as the focal point of the fixture. This pendant also features a sleek Brushed Nickel cap and stems, highlighting the industrial styling. The bottom of the fixture is enclosed with an etched glass diffuser.

Specifications:

- Brushed Nickel (-09) (plated)
- Steel Construction
- Prismatic Super White glass shade, Etched glass diffuser
- LED Module is replaceable (part # 93054049)
- Bold and striking Prismatic Glass shade.
- A sleek industrial look.
- Bottom of the fixture is enclosed with an etched glass diffuser.
- 623 lumens 69.2 lumens/watt per module (source)
- 3000K color temperature, 90+ CRI.
- Includes one 6", four 12" stems.
- 90 degree swivel
- Dimmable to 10% brightness (See Dimming Notes)
- Canopy covers a standard 4" octagonal recessed outlet box
- Mounting strap for outlet box included
- 10 feet of wire supplied
- One 6", four 12" lengths of stem included

Performance:

Number of Modules	1
Input Power	9w
Input Voltage	120 V
Input Frequency	60 Hz
Lumens/LPW (Source)	623/69.2 (LM-82)
Lumens/LPW (Delivered)	471/61.2 (LM-79)
CCT	3000 K
CRI	90 CRI
Life (hours)	60,000 (L70/TM-21)
FCC	Meets FCC Title 47, Part 15 Class B
Min. Start Temp	-30 °C
Max. Operating Temp	30 °C
Warranty	5 year warranty
Labels	cCSAus Dry location listed

P5075-0930K9

Images:



Dimensions:

Diameter: 9-1/8"
 Height: 8-1/4"
 Overall Ht. W/Stem: 74"

Glass
 Width: 7-1/16"
 Length: 7-1/16"
 Height: 5-1/4"
 Glass 2
 Width: 6-3/8"
 Length: 6-3/8"
 Height: 0-1/8"

P5075-0930K9**Dimming Notes:**

P5075 is designed to be compatible with many ELV/Reverse Phase controls.

The following is a partial list of known compatible dimmer controls.

Dimming Controls

Lutron Nova T NTELV-300

Lutron Vienti VTELV-600

Lutron Ariadni AYCL-153P

Lutron Diva DVCL-153P

Lutron Maestro MAELV-600

Lutron spacer/system SPSELV-600

Leviton Renoir II AWRMG-EAW

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.