

# WR100 | Type WR Wirewound Resistor

By Powerohm Resistors Catalog # WR100





#### **Features**

- Powerohm's Type WR Wirewound Resistors are designed for low current applications ranging from 1.0 to 32.0 amps continuous, and resistance values ranging between 250.0 and 0.25 ohms, respectively
- Can be used for any type of AC or DC power application, including motor control, dynamic braking, neutral grounding and load testing
- The corrosion resistant Type WR resistor will withstand considerable shock and vibration, qualifying it for use in most harsh environments
- Continues Wattage:324

# General

Nominal Current (A) 324
Resistance Ohms 1 Ohm

## **Dimensions**

Depth 2.75 in
Length 7.25 in
Weight 1.2 lb
Width 2 in

### **Electrical Ratings**

Current / Amperage Rating 18 A Maximum Current Rating Amps 18

Continuous

Wattage 324 W

#### **Product Assets**

