

# WR2000 | Type WR Wirewound Resistor

By Powerohm Resistors  
Catalog # [WR2000](#)



Type WR Wirewound Resistor 20 Ohms 4.6 A

## Features

- Powerohm's Type WR Wirewound Resistors are designed for low current applications ranging from 1.0 to 32.0 amps continuous, and resistance values ranging between 250.0 and 0.25 ohms, respectively
- Can be used for any type of AC or DC power application, including motor control, dynamic braking, neutral grounding and load testing
- The corrosion resistant Type WR resistor will withstand considerable shock and vibration, qualifying it for use in most harsh environments
- Continuous Wattage:423

## General

Nominal Current (A)	423
Resistance Ohms	20 Ohm

## Dimensions

Depth	2.75 in
Length	7.25 in
Weight	0.9 lb
Width	2 in

## Electrical Ratings

Current / Amperage Rating	4.6 A
Maximum Current Rating Amps	4.6
Continuous	
Wattage	423 W

## Product Assets