

WR3000 | Type WR Wirewound Resistor

By Powerohm
Catalog # [WR3000](#)



Type WR Wirewound Resistor 30 Ohms 3.4 A

Features

- Powerohm's Type WR Wirewound Resistors are designed for low current applications ranging from 1.0 to 32.0 amps continuous, and resistance values ranging between 250.0 and 0.25 ohms, respectively
- Can be used for any type of AC or DC power application, including motor control, dynamic braking, neutral grounding and load testing
- The corrosion resistant Type WR resistor will withstand considerable shock and vibration, qualifying it for use in most harsh environments
- Continues Wattage:347

General

Resistance Ohms 30 Ohm

Dimensions

Length 30 in
Weight 0.9 lb

Electrical Ratings

Current / Amperage Rating 3.4 A
Maximum Current Rating 3.4
Amps Continuous
Wattage 347 W