

WR5000 | Type WR Wirewound Resistor

By Powerohm Catalog # WR5000

Type WR Wirewound Resistor 50 Ohms 2.3 A



Features

- Powerohm's Type WR Wirewound Resistors are designed for low current applications ranging from 1.0 to 32.0 amps continuous, and resistance values ranging between 250.0 and 0.25 ohms, respectively
- Can be used for any type of AC or DC power application, including motor control, dynamic braking, neutral grounding and load testing
- The corrosion resistant Type WR resistor will withstand considerable shock and vibration, qualifying it for use in most harsh environments
- Continues Wattage:265

General

Resistance Ohms 50 Ohm

Dimensions

| Length | 50 in |
|--------|--------|
| Weight | 0.8 lb |
| | |

Electrical Ratings

| Current / Amperage Rating | 2.3 A |
|---|-------|
| Maximum Current Rating Amps Continuous | 2.3 |
| Wattage | 265 W |

