

# WR6200 | Type WR Wirewound Resistor

By Powerohm  
Catalog # [WR6200](#)



Type WR Wirewound Resistor 62 Ohms 2 A

## Features

- Powerohm's Type WR Wirewound Resistors are designed for low current applications ranging from 1.0 to 32.0 amps continuous, and resistance values ranging between 250.0 and 0.25 ohms, respectively
- Can be used for any type of AC or DC power application, including motor control, dynamic braking, neutral grounding and load testing
- The corrosion resistant Type WR resistor will withstand considerable shock and vibration, qualifying it for use in most harsh environments
- Continues Wattage:248

## General

|                     |        |
|---------------------|--------|
| Nominal Current (A) | 248    |
| Resistance Ohms     | 62 Ohm |

## Dimensions

|        |        |
|--------|--------|
| Length | 62 in  |
| Weight | 0.8 lb |

## Electrical Ratings

|   |       |
|---|-------|
| Current / Amperage Rating                 | 2 A   |
| Maximum Current Rating<br>Amps Continuous | 2     |
| Wattage                                   | 248 W |