

WR85 | Type WR Wirewound Resistor

By Powerohm Resistors
Catalog # [WR85](#)



Type WR Wirewound Resistor 0.85 Ohms 19 A

Features

- Powerohm's Type WR Wirewound Resistors are designed for low current applications ranging from 1.0 to 32.0 amps continuous, and resistance values ranging between 250.0 and 0.25 ohms, respectively
- Can be used for any type of AC or DC power application, including motor control, dynamic braking, neutral grounding and load testing
- The corrosion resistant Type WR resistor will withstand considerable shock and vibration, qualifying it for use in most harsh environments
- Continuous Wattage:307

General

Resistance Ohms 0.85 Ohm

Dimensions

Length 0.85 in
Weight 1.1 lb

Electrical Ratings

Current / Amperage Rating 19 A
Maximum Current Rating Amps 19
Continuous
Wattage 307 W

Product Assets