

3 in. x 2 in. Switch Box, Gangable, 3-1/2 in. Deep, Two 1/2 & Eight 3/4 in. KO's, Plaster Ears

By Raco Catalog # 591

3 in. x 2 in. Switch Box, Gangable, 3-1/2 in. Deep, Two 1/2 & Eight 3/4 in. KO's, Plaster Ears



- 3 in. x 2 in., 3-1/2 in. deep
- Plaster ears allow a box to be used in "old work" applications
- Gangable switch boxes offer the option of constructing a box to hold two or more devices
- With proper fitting can be used for conduit, NMSC, armored, metal clad, flex cable
- Supplied with one 1/2 in. and eight 3/4 in. knockouts
- Plaster ears allow a box to be used in "old work" applications
- 18.0 cu. in. capacity
- Acceptable for use in 2-hour fire rated walls

General

Bracket Type No Bracket

EU RoHS Indicator Contact Manufacturer

Fire Resistance Yes Gangable Yes

Knockouts 1/2 in;3/4 in

Plaster Ears Yes

Type • Switch Box

Box

UPC 050169905913 Wiring System Conduit



Dimensions

| Cubic Capacity | 18 cu.in |
|----------------|----------|
| Depth | 3.5 in |
| Height | 4.219 in |
| Weight | 0.724 lb |
| Width | 2 in |
| | |

Certifications And Compliance

Certified Listed UL Listed

Logistics

Carton Quantity 50

Packaging Type No Packaging

Pallet Quantity 2700

Product Assets

Catalogs - RACO / TayMac / Bell Full Catalog Certifications - UL COC - E195978-18

SDS - HCC_SDS

Terms and Conditions - HCC Terms & Conditions

