

2 Pole, 100/30 Amp Relay

By Trinetics
Catalog # [SERV PT-II 120V/240V 100A AL E](#)

Lighting Distribution Panel boards with Relay Control. Powered from 120/240,100 Amp Main Breaker, 2-pole, NO contacts; 120V coil. Bank of 30 amp breakers for the lighting load circuits. HOA, control circuit arresters, in a weather proof case.

Features

Available in electromagnetic or mercury tube configurations, these special order relays are variations of time proven designs. If you have a unique load, wiring or case requirement, contact Trinetics to find a relay that meets your specific lighting control need.

General

Catalog Number	SERV PT-II 120V/240V 100A AL E
Circuit Protection	C.B.



Contact	Air
Contact Configuration	N.O.
Number Of Poles	2

Electrical Ratings

Amperage Rating	100/30 A
Coil Voltage	120V
Voltage Rating	120/240 V

Product Assets

[Specifications - SERV PT-II 120V/240V 100A AL E](#)