# ASL7S - Steplights 7" Square

## TYPE

- A complete range of steplights designed for elegance in harsh environments
- Available with energy efficient LED
- Brass fascias, glass lenses and composite housings make these steplights impervious to the elements
- Features a spun, anodized aluminum parabolic reflector
- Powder coat finish in thirteen standard colors with a polymer primer sealer



ASL7S 4. OPTIONS 5. MOUNTING 1. LUMINAIRE 2. LAMP/BALLAST 3. COLOR

#### 1. LUMINAIRE

ASL7-SQ-FR (Frosted lens) ASL7-SQ-LS (Linear spread lens) ASL7-SQ-CROSS-FR (Cross with frosted lens) ASL7-SQ-CROSS-LS (Cross with linear spread lens)









ASL7-SQ-LS Linear spread lens





ASL7-SQ-CROSS-FR ASL7-SQ-CROSS-LS Linear spread lens



ASL7-SQ-EYE

### 3. COLOR

MG

I G

AGN

Standard Color		Premium Color		
WH	Arctic White	SHK	Shamrock	
BL	Black	SPP	Salt and Pepper	
BLT	Matte Black	SFM	Seafoam	
DB	Dark Bronze	WCP	Weathered	
DGN	Dark Green	Copper		
TT	Titanium	RAL	RAL 4 digit Color	
WDB	Weathered Bronze	CUSTOM	Custom Color	
MDB	Bronze Metallic			
VBU	Verde Blue			
CRT	Corten			
MAL	Matte Aluminum			

BRASS Cast brass fascia (for recessed mount only)

Medium Grey

Antique Green

Liaht Grev

#### **FASCIA DESIGNS**



Frosted



Cross



Evelid

## 4. OPTIONS

GLOW (Cast acrylic ring with a frosted finish. Adds a soft backlit glow around the perimeter of the fascia. Increases the projection of the fascia by .50"(13mm). For standard flush mount. Recessed back box only)

BSA (Housing ahead option back box with strap only for standard

## **SPECIFICATIONS**

#### HOUSING

The housing shall be one piece, molded from fiberglass impregnated, U.L. listed, sheet molding compound. The housing shall have threaded brass inserts molded into the housing to attach the cover assembly. The housing shall include a removable aluminum mounting strap to secure the housing to the structure. The semi recessed fixtures shall have an extruded aluminum outer shell, and include a cast aluminum back plate.

All internal and external hardware shall be stainless steel. The cover assembly shall consist of a die cast aluminum (or brass) frame and inner ring assembly. The cover assembly shall fully seal the housing with a molded silicone gasket. The inner fascia ring shall be rotatable to insure horizontal alignment independent of the housing. Four captive stainless steel fasteners are loosened to access the lamp and ballast assembly. The lens shall be tempered glass, frosted or with a molded linear refractor pattern. The outer sleeve for the semi recessed (SEMI) model option is extruded aluminum with a cast aluminum back plate. The standard housing is attached to the sleeve with four stainless steel screws. The assembly is then secured to the back plate with four stainless steel set screws.

For non-IC rated fixtures, fixtures must be 3" away from insulation in open walls.

## OPTICAL ASSEMBLY

The ASL7 reflector module shall be a spun. anodized aluminum parabolic reflector with a snap on lamp shield. The socket shall be vertically adjustable to change the light distribution.

#### 2. LAMP/BALLAST

LED (3LED array (5 watts). Warm white (3500K), Bright white (5100K). 120 thru 277 volt)

3I FD-WW 3I FD-BW

#### 5. MOUNTING

Standard mounting is flush mounted. Chose one of these options only if another mounting is desired.

RBX (Recessed ceiling mounting includes a rough in box and wiring compartment. Minimum 5"/125mm clearance above the ceiling)

LAMP/BALLAST	RECESSED	SEMI	RBX	GLOW
LV50	35 W	35 W	35 W	35 W
CF9 120 or 277	9 W	9 W	9 W	9 W
CF13	9 W	9 W	9 W	9 W
LED	5 W	5 W	5 W	5 W

Note: The above chart reflects wattage limitations when installed in concrete

See next page

JOB	
TYPE	
NOTES	



### **ELECTRICAL**

The ballast shall be mounted on a prewired tray with a quick disconnect plug and removed by pulling out of the housing. The ASL7 shall have a electronic transformer, 120 volt input with a 11.6 volt output to extend the lamp life. The base is a porcelain universal type to accept bi-pin or MR16 lamps. The CF9 shall use a 9 watt compact fluorescent, 2-pin lamp, electronic transformer, 120 volt. The CF13 shall use a 13-watt compact fluorescent, 4-pin lamp, electronic transformer, 120 or 277 volt. The ASL7 shall use a 3LED module (5 watt) for 120 thru 277 volt input.

### **FINISH**

The cast aluminum fascia finish consists of a five stage pretreatment regimen with a polymer primer sealer, oven dry off, and top coated with a thermoset super TGIC powder coat finish. The finish shall meet the AAMA 605.2 performance specification which includes passing a 3000 hour salt spray test for corrosion resistance. Cast brass face plates shall be supplied in a natural, unfinished state to develop a patina.

#### **CERTIFICATION**


The fixture is listed with ETL for outdoor, wet location use, UL1598 and Canadian CSA Std. C22.2 no250.

### WARRANTY / TERMS AND CONDITIONS OF SALE Download:

http://www.hubbelllighting.com/resources/warranty/


AAL reserves the right to change product specifications without notice.


#### **DIMENSIONS**



ASL7-SQ DIMENSIONS: 7.25"/184mm square

PROJECTION FROM WALL: Plain and cross: 1.0"/26mm Eyelid: 2.75"/70mm





BACK BOX STRAP: 1.50"/38mm x 13"/330mm 2 conduit holes on opposite sides .92"/23mm diameter

## ASL7S EYE LV50 WATTAGE: 50

#### LUMEN OUTPUT: 280

EFFICACY: 19

ZONE L	UMENS	%LAMP	%LUMINAIRE		UPLIGHT 32.1%
0 - 30	0.7	0.1%	0.3%		DOWNLIGHT 67.9%
0 - 40	4.0	0.4%	1.4%		
0 - 60	35	3.7%	12.5%		
60 - 90	155	16.3%	55.4%	<b>b</b>	
0 - 90	190	20.0%	67.9%	200	
90 - 180	90	9.4%	32.1%	400	
0 - 180	280	29.5%	100%	800	
				1 000	
				1 200	
				1400	

ASL7S	FR CF	9	WATTAGE: 9	LUMEN OUTPUT: 95	EFFICACY: 61
ZONE L	UMENS	%LAMP	%LUMINAIRE		UPLIGHT 40.4%
0 - 30	1.5	0.3%	1.6%		DOWNLIGHT 59.6%
0 - 40	4.5	0.8%	4.8%		+
0 - 60	19.2	3.5%	20.2%		
60 - 90	37.3	6.8%	39.4%		
0 - 90	56.5	10.3%	59.6%	10	
90 - 180	38.3	7.0%	40.4%		<del> </del>
0 - 180	94.8	17.2%	100%	20 30 40	

IES files can be found at www.aal.net

