



Primary Volts	Connect Primary Lines To	Inter- Connect	Connect Secondary Lines To				
218	X1, X2, X3	1					
213	X1, X2, X3	2					
208	X1, X2, X3	3					
203	X1, X2, X3	4					
198	X1, X2, X3	5					
Secondary Volts							

Secondary voits									
480			H1, H2, H3						
277 1 phase			H1 to H0 H2 to H0 H3 to H0						

NOTE:
PRIMARY AND SECONDARY BUS AREA
IN FRONT OF CASE.

KVA	CATALOG NUMBER		VOLTAGE		LUG KIT	WEIGHT		PHASE		FREQUENCY			
				LOW	HIGH								
225	T3225K0034B		208Δ	480Y/2	77		1500 Lbs			3ф	60Hz		
Temp Rise	2: 150°C TYPICAL PERFORMANCE DATA								Typical Efficiency @ 35%		98.94%		
Insulation	:	220°C	Regulation @ 1.60% Windings: AL			Typical No Load Losses:		475.41					
NEMA ST2 Standard:	NEMA ST20 Standard: 55 d			Standards:	UL/CSA		Impedanc		o 1 4 41% 1 1		100% Load (Typ) Load Losses (I ² R)		3964.61
Electrosta Shield:	tic	Option		Approvals:	DOE-16		Enclosure		3R		Total Load Lossess:		4440.02

Meets US DOE 2016 Efficiency

REVISIONS

NOTES:

- 1. Dry Type
- 2. Class AA
- 3. Ventilated
- 4. Paint #61 ANSI



DATE: 14-Aug-13

TYPE NO:

CASE 4